

## THE LEADER IN MICROWAVE ANTENNA INNOVATION

1.8 m | 6 ft Standard Performance Parabolic Reflector Antenna, Dual-polarized, 5.725-7.125GHz

### **SPD6-6**



The SP Standard Performance Series by RadioWaves offers a full line of cost effective standard performance parabolic antennas engineered to deliver reliable radio links. Designed for both unlicensed and licensed band applications, RadioWaves field-proven preassembled SP antennas and robust pole-mounts ensure "set and forget" installation with minimal post-installation maintenance. If it's rugged, it must be RadioWaves!

### **FEATURES AND BENEFITS**

O Standard Performance Parabolic Antennas – Excellent performance for a wide range of licensed and unlicensed applications O Fully Preassembled at the Factory – Simplifies installation on site and guarantees "factory-tested" quality

### **SPECIFICATIONS**

### General

| Antenna Type  | Standard Performance Parabolic Reflector Antenna |
|---------------|--|
| Size, nominal | 6 ft   1.8 m                                     |
| Polarization  | Dual   |

| Standard RF Connector Type   | CPR137G                            |
|------------------------------|------------------------------------|
| Standard RF Connector Suffix | RS (append suffix to model number) |

### **Electrical**

| Operating Frequency Band          | 5.725 - 7.125 GHz |
|-----------------------------------|-------------------|
| Half Power Beamwidth, Horizontal  | 1.9 degrees       |
| Half Power Beamwidth, Vertical    | 1.9 degrees       |
| Cross-Polarization Discrimination | 30 dB             |
| Front to Back Ratio (F/B)         | 46 dB             |

| Gain, Low Frequency  | 38.2 dBi |
|----------------------|----------|
| Gain, Mid Frequency  | 39.3 dBi |
| Gain, High Frequency | 39.8 dBi |
| VSWR                 | 1.37:1   |
| Return Loss          | -16.1 dB |



# THE LEADER IN MICROWAVE ANTENNA INNOVATION

### Mechanical

| Fine Azimuth<br>Adjustment       | +/- 10 degrees     |                                     |
|----------------------------------|--------------------|-------------------------------------|
| Fine Elevation<br>Adjustment     | +/- 25 degrees     |                                     |
| Mounting Pipe<br>Diameter, Min   | 4.5 inch   11.4 cm |                                     |
| Mounting Pipe<br>Diameter, Max   | 4.5 inch   11.4 cm |                                     |
| Net Weight                       | 95 lbs   42.8 kg   | 125 lbs   56.3 Kg with<br>RD radome |
| Wind Velocity<br>Operational     | 90 mph   145 km/h  |                                     |
| Wind Velocity<br>Survival Rating | 125 mph   201 km/h |                                     |

| Mechanical<br>Configuration                        | SP6                   |                                      |
|--|-----------------------|--------------------------------------|
| Axial Force (FA)                                   | 1768 lbs   7865 N     | 973 lbs   4329 Nm<br>with RD radome  |
| Side Force (FS)                                    | 98 lbs   436 N        | 162 lbs   721 Nm with<br>RD radome   |
| Twisting Moment (MT)                               | 2270 ft-lbs   3077 Nm | 2100 lbs   2847 Nm<br>with RD radome |
| Operating Temperature Range                        | -40 to +60 C          |                                      |
| Max Pressure, PSIG,<br>(if waveguide<br>interface) | 5                     |                                      |

# **Regulatory Compliance**

| FCC                        | Part 101 Cat. B1 |
|----------------------------|------------------|
| Industry Canada Compliance | SRSP305.9B       |

| ETSI           | 302217 R1 C1 |
|----------------|--------------|
| RoHS-compliant | Yes          |

# **Shipping Information**

| Package Type | Wood Crate         |
|--------------|--------------------|
| Gross Weight | 222 lbs   100.7 kg |

| Dimensions, L x W x H | 0 x 0 x 0in   0 x 0 x 0 cm |
|-----------------------|----------------------------|
| Shipping Volume       | 0 cu ft   0 cu m           |

<sup>\*</sup>Additional OEM interfaces and adapters may be available. Contact RadioWaves for a complete and current list of available adapters.





## **TECHNICAL DRAWINGS**



